

# Tactical Table

How It Works/ Product Information Installation Instructions and Videos Safety Rules Troubleshooting

Congratulations on your decision to purchase a Tactical Trap. You've made a wise decision and we're grateful you've given us the opportunity to serve you as a customer.

If you have any questions about your product don't hesitate to contact our support team via email at support@tacticaltraps.com.

### Step 1: What's included?


Included with your Tactical Table should be...















2 Keycards

Buzzer setting card

LED light (circle or strip)

Foam insert

batteries, not included)

If your package is missing any of these items please email us at support@tacticaltraps.com

## Step 2: Assemble the Table

Your Tactical Table has an instruction sheet with illustrations included for quick assembly. Use that sheet along with the 12 bolts and allen wrench to assemble the table.

#### Step 3: How the Tactical Table Works

Your unit is equipped with a Bluetooth enabled RFID locking system and emergency battery backup. Included with your unit are 2 RFID keycards and 1 sound card. You can find those taped to the bottom of your unit in a yellow envelope. (Save the 4-digit pin on the envelope, you'll need this to connect to Bluetooth).

To open the table, place any one of the keycards included over the orange sticker dot on the top of your table. The lock will automatically disengage and drawer will drop open.

It is engineered to drop open when assembled and may not do that while laying flat.

To close the table, wait 3 seconds for the latch to automatically reset and then just gently slide the drawer in and push until it latches closed.

NOTE: Pay no attention to how the keycards are labeled (manager/user) ...they all work the same. They are labeled that way for programming which we did for you.

Also, the keycards included can be hidden (or attached by using double sided tape) under any decor you choose to place on top of your table or in a wallet, so you don't have to worry about misplacing them. DO NOT CUT the cards in any way, it will deactivate them.

## Buzzer Setting/Sound Card:

The lock is equipped with a beeping noise to let you know if the unit is not secure. One swipe/scan of the sound card will disable the beep, another swipe will restore the beep.

NOTE: Please make sure to leave the sound on until you're familiar with the lock trigger point (marked with the orange sticker). You can remove the orange sticker dot after you get used to where the trigger point to open the lock is located.

#### Step 4: How the Bluetooth Lock Works

In this step you'll need the 4- digit pin from the yellow keycard envelope to connect the lock to the Bluetooth app. This 4-digit pin is also printed on the face of your lock but can be harder to see there. We recommend keeping the yellow envelope in a safe place for future use.

#### With Your Phone:

Step 1: Update your phones software if possible

Step 2: Restart your phone

Step 3: Turn on your Bluetooth



Step 4: Go to the app store or google play and search Tactical Traps. Install the app

Step 5. After you download the app, open it up and click the Bluetooth connect button. Your phone will scan for the lock. When it's found enter your 4-digit pin number. You can find this number written on top of the envelope your keycards came in. It's also located on the face of the lock inside your barrel head.

Step 6: Click the unlock button after the app is installed and Bluetooth is connected to open your table. Also, you can check your battery voltage and silence the beep by clicking the three lines in the right corner of the app.







## Step 5: Batteries


The RFID lock runs on 4 AAA batteries that should be changed about every 6 months. To change the batteries simply remove the thumb screw (black knob) from the lock and then open the battery cover. Remove all 4 AAA batteries, leave batteries out with unit open for 30 minutes and then reinstall 4 fresh high alkaline batteries. You will then close the battery cover and screw the thumbscrew back in.


Important: Please install 4 new high alkaline AAA batteries into the lock before mounting. Also, make sure the internal battery backup wire is firmly attached to the lock before closing.

#### Step 6: Battery Backup Pack

If for some reason the batteries in your lock die before you change them – no problem! You can always get to your guns by using the battery backup pack that came with your purchase. Here's what you do:

- 1. Install 4 AAA batteries inside the battery backup pack.
- 2. Locate the small auxiliary hole on the right of the table.
- 3. Plug the backup pack into the hole as tightly as it will fit.
- 4. Scan one RFID card over the lock trigger point (where the orange dot sticker was) just like you normally would, and your table will open.
- 5. When your unit is open, change your lock batteries.
- 6. Remove the batteries from the backup pack and store it outside of the table.






#### Step 7: LED light

The included LED light is motion detected, meaning there isn't an on/off switch. When the table is closed the light will shut off. When it opens it will turn on by itself.

To mount your light, you will peel and stick either the long magnet (strip light) or the small round sticker (round light) on the top/inside of the table, making sure it's placed away from the lock. Both lights are upgraded versions; we send the style of light based on what our vendor has sent us.



## Step 8: Cutting the Foam to Fit Your Accessories

Note: For a video walk through, go to TacticalTraps.com/install

Lay the foam insert flat on a table. MAKE SURE ALL OF YOUR FIREARMS ARE UNLOADED AND THE CHAMBER IS EMPTYI Lay your gear on top of the foam however you want. Push down snugly and trace around the outside of the items using a marker.

Then cut the foam carefully using a sharp razor/utility knife. We recommend you cut at least  $^3\!\!4$  of the foam for a handgun.



The more time you take to do this correctly, the better your gear will fit. Once you have your cutout made, remove the adhesive backing and carefully place it into your table, making sure it is lined up correctly.



NOTE: The more cavities you cut out, the less adhesive backing you will have to hold your gear in place. Overloading it is counterproductive; never exceed 15lbs of gear inside. This isn't a storage bin!

#### Step 9: Safety Rules to Consider

1. Don't store your firearm with a live round in the chamber. Remember a tactical trap is not a safe; and although it's sturdy and well-built, it can be knocked off the wall or broken with enough force.

In the unlikely event of that happening your gun could send a round through your house after being dropped! Yes, many new firearms are equipped with a drop safety to prevent this, but this is still something you should consider especially if you live in a home with children. You can take back a lot of things in life but a bullet is not one of them. Please remember that and be responsible when you store your gear.

- 2. If you have children living in your home it would be a good idea to move your firearms into a locked safe when you are not home or by your Tactical Trap. Most children will not understand how to work the product, but it's better to be safe than sorry. Plus, the whole purpose of a Tactical Trap is for quick access and if you're not home or by the unit... it makes no sense to leave your firearm inside of it.
- 3. Our products are designed to blend in as ordinary pieces of furniture and are strong enough to hold knick-knacks, candles, small vases, etc.... the normal items you might see on an ordinary table.

They are not designed to hold up a TV or anything heavy! Use common sense with decorating your table. If you think an item you want to place on your unit might be too heavy...then it probably is. Also, don't store more than 15lbs of gear inside the unit. That's more than enough weight to hold a couple of handguns, spare mags and a flashlight.

4. Even though it takes around 300lbs of force to pry the unit open...it is not intended to serve as a substitute for a government-regulated gun safe. A lock, any lock in the world including a bank vault can fail. Is it likely? No, but neither is lighting striking you, but it can happen. If you have really young children living or visiting your home...don't allow them to play on the Tactical Table. If you have older children living or visiting the house that you don't want messing around with your guns...take them out of the unit when you're not home and lock them in a safe. Use common sense when storing your firearms and you'll be just fine.

#### Step 10: Troubleshooting

#### Q: My table won't close.

A: No problem, we have a quick fix! Please go to our video page: http://www.tacticaltraps.com/install and watch the new video our manager just uploaded titled Tactical Table Won't Shut. The black box inside your table just needs a little bit of an extra 'push' backwards with your thumb for it to line up with the locking mechanism and latch into please. Please let us know if this helps.

#### Q: My table won't open.

A:You might need to apply slight upward pressure to the bottom to disengage the lock. This is perfectly normal.

#### Q: Where is the battery backup port located?

When standing in front of the table, it is on the RIGHT side of the black box mounted under the table. You can run your hand along side the black box to feel the auxiliary port. It is meant to be discreet so it isn't easy to spot. If you forget to change your lock batteries and your table won't open, insert 4 AAA batteries into the pack and plug it into this port. Then scan the RFID card or use the Bluetooth option to open the table. Once open, immediately change the 4 AAA batteries inside your lock (use alkaline batteries.)

#### Q: How do I get a part that was missing with my order?

A: Email support@tacticaltraps.com Other questions not answered here? Check TacticalTraps.com/faqs

#### Contact Us:

support@tacticaltraps.com (800)651-9171

**Legal Disclaimer:** Misuse of products sold by Tactical Traps can involve serious risks including injury, disability and death. Purchasers assume all risks.